



16 port 10/100/1000Mbps Network Switch

SN-1016G



www.uncuguvenlik.com.tr

Overview

SN-1016G, with 16 10/100/1000M auto-negotiation RJ45 port is designed independently by Shenzhen Fengrun Technology Co., Ltd for Cafe, enterprise, school and intelligent community.

Key features

Support 16 10/100/1000M auto-negotiation RJ45 port

Support IEEE 802.3x Flow Control for full-duplex and back pressure for half-duplex

Technical Specification

Products Specifications		SN-1016G
Standards and Protocols		IEEE 802.3, IEEE 802.3U
		IEEE 802.3ab, IEEE 802.3x
Ports		16 10/100/1000M RJ45 port
Indicators	Each port	Link/Ack
	Each device	Power
Features	Stored and forward	Support
	Bandwidth	36Gbps
	MAC address	8K
Operating Environment		Operating Temperature: 0°C ~ 40°C (32°F ~ 104°F) Storage Temperature: -40°C ~ 70°C (-40°F ~ 158°F) Operating Humidity: 10% ~ 90% RH (non-condensing) Storage Humidity: 5% ~ 90% RH (non-condensing)
Input Power		100-240V, 50/60Hz

Demerions (L×W×H)

440mm×180mm×44mm

User Guide:

1.Check the Network switch

(1)Please check the enclosure,RJ45 ports,LED indicators ,sure they are ok,

(2)Connect the Network switch with power,make sure the initialization of Network switch is available as below:

POW indicator is off at the beginning when power connected

POW indicator is on and keeps

Other indicators will be on ,then off after one or two seconds

2.Connection cables:

- ① Connected the Switch to Computer or other PD(like IP camera, wireless AP) by CAT5 or 6 cables
- ② Connected the external power adapter to Switch and the power cord to AC plug
- ③ Turn on the switch

Caution:

- 1) All operation should be provided only by a qualified service technician
- 2) Please avoid any heavy thing placed on the Device.
- 3) Do not use this product near water, for example, in a wet basement or near a swimming pool
- 4) For outdoor use, the device itself should be housed inside a protective enclosure.
- 5)Cutting power during a firmware upgrade can damage your device.
- 6)Only use attachments/accessories specified by the manufacturer.
- 7)Opening the switch or tampering with the warranty sticker can void your warranty.